

## LA1 External Annunciator

- The LA1 External annunciator contains a very loud 119db alarm and a bright red Xenon tube flasher to get attention in the event of an alarm condition. The annunciator is controlled by any output of the LA1 AC Power Supply.



### EXTERNAL ANNUNCIATOR FEATURES

- 119 dB super loud audible alarm
- Xenon flash tube bright visual alarm beacon
- Super durable NEMA-4X cast aluminum CNC machined enclosure
- Stainless steel mounting hardware
- Operates on 110 or 220 volts AC
- Can be mounted anywhere outside the intrinsically safe area
- Controlled by any output of the LA1 AC power supply
- 2 YEAR WARRANTY

### SPECIFICATIONS

SPECIFICATIONS	
Materials:	Heavy Duty Cast Aluminum 316 stainless steel hardware
Input Voltage:	90 to 260 volts AC
Current Draw:	0.25 Amps @ 120VAC
Operating Temp.	-40 to 150F
Siren Output Volume	119dB @ 10 ft.
Visual Indicator	Xenon flash tube with red lens
Conduit Connection	3/4" Threaded conduit fitting
Cabinet Dimensions	10.24h x 6.3w x 3.56d
Overall dimensions	10.24h x 6.3w x 7.5d

### PART NUMBERS

PART NUMBERS	
Model Number:	Description:
LA1-EXA-110-A	LA1 External Annunciator, 110vac, Revision A



**Integrated Control Systems Inc.**  
 1425 American Way, Cedar Hill, TX. 75104  
 PH: (972) 291-6064  
 FAX: (972) 291-5975  
[WWW.INTCONSYS.COM](http://WWW.INTCONSYS.COM)

For more information, please visit our website at:

[WWW.INTCONSYS.COM](http://WWW.INTCONSYS.COM)