

ES1 Emergency Pump Stop Switch

- An emergency stop switch is required by electrical code to shut off all fueling operations in the event of an emergency. (NFPA 30a, CH4, Section 4-1.2)



The ES1 switch is designed to fulfill the NFPA code requirements. It uses a heavy cast aluminum, weather sealed, NEMA 4X enclosure with stainless steel hardware. The switch is a large (40mm) red, single or double pole, 10 amp normally closed unit. The ES1 has a highly visible, bright yellow sign on the front panel for easy identification in an emergency. All components of the ES1 are UL listed.

SPECIFICATIONS

CABINET		SWITCH	
Material:	Heavy Duty Cast Aluminum	Type:	Normally Closed SPST or DPST
Hardware:	Stainless Steel	Rating:	10A@120VAC or 6A@240VAC
Classification:	NEMA 4X – weather sealed	MTBF:	10,000 Operations
Listings:	UL (US and Canada)	Listings:	UL (US & Canada) CE
Case Size:	4.5" x 3.5" x 1.25"		

MODEL NUMBERS

Model Number:	Description:
ES1-SP	ES1 with single pole switch
ES1-DP	ES1 with double pole switch

Integrated Control Systems Inc.

1425 American Way, Cedar Hill, TX. 75104

Voice: (972) 291-6064

Fax: (972) 291-5975

www.intconsys.com

For more information, please visit our website at:

WWW.INTCONSYS.COM